



Upgrading Edge75MXP to Edge95MXP

Edge75MXP requires several steps to upgrade product type.

Note) Before you begin, make sure you have the product id key which contains 16 digits of number.
If not, please open a new SR request for this key.

Installing product key over CLI

Access to your endpoint ether from console, telnet or ssh, then execute below.
After the reboot, changes can be confirmed from GUI.

```
> productkey "16-digits-number key"  
> xcommand boot
```

Installing product key over WEBGUI

There is another choice over WEBGUI to enable the product id key.

Note) You need at least F9.0.1 to have this access.

From the same page you can also swap PAL to NTSC (or vice versa if needed)

<http://<IP Address of your Edge MXP>/setproductversion.ssi>

Set Product Version

System Information	
Product ID	TANDBERG Edge 95MXP
Software Version	F9.3 NTSC
Hardware Serial Number	26B10746
Current Product Key	1838045602357169

Camera setting

Camera type (NTSC) Change require reboot to activate

Product Option

Product Key

Installing other options

You should now add any option keys from GUI or from API console (telnet, ssh, serial).

Example from CUI

New option : xConfiguration OptionKey Features: "16-digits-number key"

Bandwidth option : xConfiguration OptionKey Bandwidth: "16-digits-number key"