



Linksys Phone Adapter Configuration

Router - **Voice**

Info | System | SIP | Provisioning | **Regional** | FXS 1 | FXS 2 | Line 1 | Line 2 | Line 3 | Line 4

[PBX Status](#)  
[User Login](#) | [basic](#) | [advanced](#)

Call Progress Tones

Dial Tone: 350@-19,440@-19;10(\*0/1+2)  
 Second Dial Tone: 420@-19,520@-19;10(\*0/1+2)  
 Outside Dial Tone: 420@-16;10(\*0/1)  
 Prompt Tone: 520@-19,620@-19;10(\*0/1+2)  
 Busy Tone: 480@-19,620@-19;10(.5/.5/1+2)  
 Reorder Tone: 480@-19,620@-19;10(.25/.25/1+2)  
 Off Hook Warning Tone: 480@-10,620@0;10(.125/.125/1+2)  
 Ring Back Tone: 440@-19,480@-19;\*(2/4/1+2)  
 Confirm Tone: 600@-16;1(.25/.25/1)  
 SIT1 Tone: 985@-16,1428@-16,1777@-16;20(.380/0/1,.380/0/2,.380/0/3,0/4/0)  
 SIT2 Tone: 914@-16,1371@-16,1777@-16;20(.274/0/1,.274/0/2,.380/0/3,0/4/0)  
 SIT3 Tone: 914@-16,1371@-16,1777@-16;20(.380/0/1,.380/0/2,.380/0/3,0/4/0)  
 SIT4 Tone: 985@-16,1371@-16,1777@-16;20(.380/0/1,.274/0/2,.380/0/3,0/4/0)  
 MWI Dial Tone: 350@-19,440@-19;2(.1/.1/1+2);10(\*0/1+2)  
 Cfwd Dial Tone: 350@-19,440@-19;2(.2/.2/1+2);10(\*0/1+2)  
 Holding Tone: 600@-19;\*(.1/.1/1,.1/.1/1,.1/9.5/1)  
 Conference Tone: 350@-19;20(.1/.1/1,.1/9.7/1)  
 Secure Call Indication Tone: 397@-19,507@-19;15(0/2/0,.2/.1/1,.1/2.1/2)  
 Feature Invocation Tone: 350@-16;\*(.1/.1/1)

Distinctive Ring Patterns

Ring1 Cadence: 60(2/4)	Ring2 Cadence: 60(.8/.4,.8/4)
Ring3 Cadence: 60(.4/.2,.4/.2,.8/4)	Ring4 Cadence: 60(.3/.2,1/.2,.3/4)
Ring5 Cadence: 1(.5/.5)	Ring6 Cadence: 60(.2/.4,.2/.4,.2/4)
Ring7 Cadence: 60(.4/.2,.4/.2,.4/4)	Ring8 Cadence: 60(0.25/9.75)
Ring9 Cadence: 60(.4/.2,.4/2)	

Distinctive Call Waiting Tone Patterns

CWT1 Cadence: 30(.3/9.7)	CWT2 Cadence: 30(.1/.1,.1/9.7)
CWT3 Cadence: 30(.1/.1,.1/1,.1/9.7)	CWT4 Cadence: 30(.1/.1,.3/1,.1/9.3)
CWT5 Cadence: 1(.5/.5)	CWT6 Cadence: 30(.1/.1,.3/.2,.3/9.1)
CWT7 Cadence: 30(.3/.1,.3/.1,.1/9.1)	CWT8 Cadence: 2.3(.3/2)
CWT9 Cadence: 30(.3/9.7)	

Distinctive Ring/CWT Pattern Names

Ring1 Name: Bellcore-r1	Ring2 Name: Bellcore-r2
Ring3 Name: Bellcore-r3	Ring4 Name: Bellcore-r4
Ring5 Name: Bellcore-r5	Ring6 Name: Bellcore-r6
Ring7 Name: Bellcore-r7	Ring8 Name: Bellcore-r8
Ring9 Name: Bellcore-r9	

Ring and Call Waiting Tone Spec

Ring Waveform: Trapezoid	Ring Frequency: 20
Ring Voltage: 85	CWT Frequency: 440@-10

**Control Timer Values (sec)**

Hook Flash Timer Min:	.1	Hook Flash Timer Max:	.9
Callee On Hook Delay:	0	Reorder Delay:	5
Call Back Expires:	1800	Call Back Retry Intvl:	30
Call Back Delay:	.5	VMWI Refresh Intvl:	0
Interdigit Long Timer:	10	Interdigit Short Timer:	3
CPC Delay:	2	CPC Duration:	0

**Vertical Service Activation Codes**

Call Return Code:	*69	Call Redial Code:	*07
Blind Transfer Code:	*98	Call Back Act Code:	*66
Call Back Deact Code:	*86	Call Back Busy Act Code:	*05
Cfwd All Act Code:	*72	Cfwd All Deact Code:	*73
Cfwd Busy Act Code:	*90	Cfwd Busy Deact Code:	*91
Cfwd No Ans Act Code:	*92	Cfwd No Ans Deact Code:	*93
Cfwd Last Act Code:	*63	Cfwd Last Deact Code:	*83
Block Last Act Code:	*60	Block Last Deact Code:	*80
Accept Last Act Code:	*64	Accept Last Deact Code:	*84
CW Act Code:	*56	CW Deact Code:	*57
CW Per Call Act Code:	*71	CW Per Call Deact Code:	*70
Block CID Act Code:	*67	Block CID Deact Code:	*68
Block CID Per Call Act Code:	*81	Block CID Per Call Deact Code:	*82
Block ANC Act Code:	*77	Block ANC Deact Code:	*87
DND Act Code:	*78	DND Deact Code:	*79
CID Act Code:	*65	CID Deact Code:	*85
CWCID Act Code:	*25	CWCID Deact Code:	*45
Dist Ring Act Code:	*26	Dist Ring Deact Code:	*46
Speed Dial Act Code:	*74	Secure All Call Act Code:	*16
Secure No Call Act Code:	*17	Secure One Call Act Code:	*18
Secure One Call Deact Code:	*19	Conference Act Code:	
Attn-Xfer Act Code:		Modem Line Toggle Code:	*99
FAX Line Toggle Code:	#99	Media Loopback Code:	*03

Referral Services Codes:

Feature Dial Services Codes:

**Vertical Service Announcement Codes**

Service Annc Base Number:

Service Annc Extension Codes:

**Outbound Call Codec Selection Codes**

Prefer G711u Code:	*017110	Force G711u Code:	*027110
Prefer G711a Code:	*017111	Force G711a Code:	*027111
Prefer G723 Code:	*01723	Force G723 Code:	*02723
Prefer G726r16 Code:	*0172616	Force G726r16 Code:	*0272616
Prefer G726r24 Code:	*0172624	Force G726r24 Code:	*0272624
Prefer G726r32 Code:	*0172632	Force G726r32 Code:	*0272632
Prefer G726r40 Code:	*0172640	Force G726r40 Code:	*0272640
Prefer G729a Code:	*01729	Force G729a Code:	*02729

**Miscellaneous**

Set Local Date (mm/dd):		Set Local Time (HH/mm):	
Time Zone:	GMT-06:00 <input type="text"/>	FXS Port Impedance:	600 <input type="text"/>
Daylight Saving Time Rule:	start=3/8/7;end=11/1/7;save=1		
Daylight Saving Time Enable:	yes <input type="checkbox"/>	FXS Port Input Gain:	-3 <input type="text"/>

FXS Port Output Gain:	-3	DTMF Playback Level:	-16
DTMF Playback Length:	.1	Detect ABCD:	yes
Playback ABCD:	yes	Caller ID Method:	Bellcore(N.Amer,China)
Caller ID FSK Standard:	bell 202	Feature Invocation Method:	Default
More Echo Suppression:	no		

Undo All Changes

Submit All Changes

[PBX Status](#)

[User Login](#) | [basic](#) | [advanced](#)

Copyright © 1992-2006 Cisco Systems, Inc. All Rights Reserved.