



Cisco Software: Cisco ONE EA-Lizenzübertragung

Kurzreferenz

Cisco ONE EA-Lizenzübertragung

Wir möchten unseren Partnern und Direktkunden die Cisco ONE EA-Lizenzportierung erleichtern, indem Anfragen über EA Workspace (EAWS) verarbeitet werden. Lizenzportierung bedeutet, dass eine Lizenz von einem Gerät zu einem anderen verschoben wird und das Zielgerät über eine andere Stufe/Version verfügt.

EA-Kunden können in einem gültigen Übertragungsszenario eine zuvor erstellte Lizenz von einem Gerät auf ein anderes Gerät übertragen. Dies wird im EAWS nicht als zusätzliche Nutzung festgehalten.

Im EAWS wird der Kunde anhand von vier Schritten durch den Portierungsprozess geleitet: Zielgerät auswählen, Funktionen auswählen, Lizenz verifizieren und Lizenz überprüfen.

Cisco ONE EA-Lizenzübertragung

- 1 Melden Sie sich beim Enterprise Agreement Workspace (EAWS) an und wählen Sie einen geeigneten Smart Account oder Virtual Account aus.
- 2 Wählen Sie im Hauptmenü die Registerkarte „Devices“ (Geräte) aus.

The screenshot displays the Cisco Software Central interface for Enterprise Agreements. The top navigation bar includes 'Smart Account' (TestELADemo) and 'Virtual Account' (CiscoELA- CiscoONE). The main menu has 'Devices' highlighted. Below the menu is a search bar and an 'Add New Devices' button. The main content area contains a table with the following data:

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action
test host name...		Mac Address HOSTNAME=76546789		0	0	0	Action
Not Specified	AMP7150	License Key 12:32:46:76:54:33:24		5	5	5	Action
Shivani final	Virtual	Mac Address HOSTNAME=732498274873247234	test final	0	0	0	Action
test 3		Mac Address 234324234324	test 3	0	0	0	Action
Shivani test11	Virtual	Mac Address 3243242434432443	test 11	0	0	0	Action
test 1234		Mac Address 823868326872648324	test 1234	0	0	0	Action
shivani test 4		Mac Address 8739879821739721	test 4	0	0	0	Action

Cisco ONE EA-Lizenzübertragung

- 3 Klicken Sie in der Zeile für das Quellgerät auf das Dropdown-Menü „Action“ (Aktion). Dies ist das Gerät, dessen Lizenz Sie übertragen möchten.
- 4 Wählen Sie im Dropdown-Menü „License Transfer“ (Lizenzübertragung) aus, um die Transaktion zur Lizenzübertragung zu starten.

The screenshot shows the Cisco Software Central / Enterprise Agreements interface. The top navigation bar includes "Enterprise Agreements", "Smart Account", and "Virtual Account CiscoELA-CiscoONE". Below this is a secondary navigation bar with tabs for "EAs", "Devices", "Transactions", "Provisioning Requests", "RTU Transactions", "Reports", "Preferences", "Help", and "Customer Support". The "Devices" tab is active.

Below the navigation is a search bar labeled "View Devices" with the placeholder text "Search Device(s) Name Or Identifiers Or Device(s) Description" and a search icon. To the right of the search bar is a blue button labeled "Add New Devices".

The main content area displays a table of devices. The table has the following columns: "Device Name", "Model Number", "Device Identifiers", "Device Description", "Transactio...", "Licens...", "Features", and "Action".

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action
Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2	2	Action ^
Ajlinkya	Catalyst 4500 ...	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0CZ	Testing	0	0	License RMA
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DJ		1	1	License Transfer
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DU		0	0	License Resend
Not Specified	ASR1002-HX	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2324Q2CH		1	1	License Download
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2338Q0PT		0	0	Edit Device
							Update Model
							Action v

The "Action" dropdown menu for the first row is open, showing options: "License RMA", "License Transfer", "License Resend", "License Download", "Edit Device", and "Update Model". The "License Transfer" option is highlighted. Red circles with numbers 3 and 4 are overlaid on the image to indicate the steps described in the text.

Cisco ONE EA-Lizenzübertragung

Hinweis: Wenn das von Ihnen ausgewählte Gerät über keine Lizenzfunktionen zum Portieren verfügt, enthält das Menü „Action“ (Aktion) keine Lizenzoptionen.

Cisco Software Central / Enterprise Agreements

Enterprise Agreements

Smart Account Virtual Account
CiscoELA-CiscoONE

EAs Devices Transactions Provisioning Requests RTU Transactions Reports Preferences Help Customer Support

View Devices | Search Device(s) Name Or Identifiers Or Device(s) Description [Add New Devices](#)

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action	
Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2	2	Action	
Ajinkya	Catalyst 4500 ...	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0CZ	Testing	0	0	0	Action
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DJ		1	1	1	Action
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DU		0	0	0	Action
Not Specified	ASR1002-HX	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2324Q2CH		1	1		<div style="border: 2px solid red; padding: 5px; display: inline-block;">Edit Device Remove Device</div>
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2338Q0PT		0	0		
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DN		1	1	1	Action

Cisco ONE EA-Lizenzübertragung

- 5 Wählen Sie das Zielgerät aus. Dies ist das Gerät, auf das Sie die Lizenz des Quellgeräts portieren möchten.
- 6 Jetzt können Sie die Lizenzfunktionen des Quellgeräts auswählen, die auf das Zielgerät übertragen werden sollen. Klicken Sie auf die Schaltfläche „Next“ (Weiter), um mit Schritt 2 fortzufahren.

The screenshot shows the 'License Transfer' window with a progress bar at the top indicating four steps: 1. Select Target Device, 2. Select Features, 3. Verify License, and 4. Review. Below the progress bar, the text reads 'Transfer Licences from one device to another device registered with your Cisco Profile.' Under 'Selected Source Device', the Serial Number is 23. The 'Select Target Device' section includes a search bar and an 'Add New Devices' button. A table lists target devices with columns for Device Name, Model Number, Device Identifiers, Device Description, Transacti..., and Lice... The second row is selected and highlighted with a red box, and a red circle with the number 5 is next to it. At the bottom right, there are 'Cancel' and 'Next' buttons, with a red circle and the number 6 next to the 'Next' button.

License Transfer

1 Select Target Device 2 Select Features 3 Verify License 4 Review

Transfer Licences from one device to another device registered with your Cisco Profile.

Selected Source Device:

Serial Number
23

Select Target Device

Select or Add New Target on which you want to transfer your license.

Search Devices Add New Devices

Device Name	Model Number	Device Identifiers	Device Description	Transacti...	Lice...
<input type="radio"/> Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2
<input checked="" type="radio"/> Not Specified	N9K-C93240...	Serial Number FDO233305XC		0	0
<input type="radio"/> Not Specified	N9K-C93240...	Host ID		1	1

Cancel Next

Cisco ONE EA-Lizenzübertragung

- 7 Wählen Sie die Lizenzfunktionen aus, die Sie vom Quellgerät portieren möchten.
- 8 Klicken Sie auf die Schaltfläche „Next“ (Weiter), um mit Schritt 3 fortzufahren und zu verifizieren, dass die Lizenz übertragen werden soll.

License Transfer

Transfer Licences from one device to another device registered with your Cisco Profile.

Selected Source Device:

Target Device:

Select Products and Features

Select Products for which you want to transfer license from.

<input type="checkbox"/>	Feature Name	Product Family	Available Qty	Qty	Trans Date
<input checked="" type="checkbox"/>	MDS_MFGINSTALL	Nexus 4000 Series S...	1	1	2018-Feb-9

Back Cancel **Next**

Cisco ONE EA- Lizenzübertragung

- 9 Verifizieren Sie die Lizenz, das Quellgerät und das Zielgerät. Nach der Lizenzübertragung befinden sich die ausgewählten Lizenzen auf dem Zielgerät.
- 10 Verifizieren Sie den Endbenutzer und den Empfänger und bearbeiten Sie die Angaben, falls erforderlich.
- 11 Aktivieren Sie das Kontrollkästchen, um den Lizenzbedingungen zuzustimmen.
- 12 Klicken Sie auf „Submit“ (Senden).

License Transfer

Progress: 1. Select Target Device (✓), 2. Select Features (✓), 3. Verify License (●), 4. Review (●)

Transfer Licences from one device to another device registered with your Cisco Profile.

UDI Product ID	UDI Version ID	UDI Serial Number	UDI Product ID	UDI Serial Number	UDI Version ID
ISE-VM-K9	V03	FTX12448902	CISCO8765	12765456987	V67

Post License Transfer, selected licenses will be transferred to target device.

Features
License Transfer will be done for the following Features

Prod Desc	SKU	L...
Identity Services Engli...	L-ISE-BSE-100=	1

User Preferences

Please provide preferences to generate license or request activation.

Notes

Send To * End User *

Include License as an email attachment. I agree with Terms of the License [View License Agreement...](#)

Buttons: Back, Cancel, Submit

Cisco ONE EA-Lizenzübertragung

Die Verifizierung der Lizenzportierung wird angezeigt.

- 13 Klicken Sie auf die Schaltfläche „Download“ (Herunterladen), wenn Sie die Software herunterladen möchten.
- 14 Klicken Sie auf die Schaltfläche „Done“ (Fertig), um die Lizenzportierung abzuschließen.

License Request Status
The license has been sent to [isc@cs.com](#)

13 [Download](#)

Thank you for registering your product with Cisco Systems. If you have not received an email within 1 to 3 hours, please open a Service Request using the **EA Licensing Ops Concierge** at [https://cisco.com/go/eaops](#).

Use the following transaction ID to view status on the Transactions page.

Transaction ID:TRXREQEPDHXPSXX - more details are available in the Transactions menu section.

Note : Check that Junk/Spam email folders allow email from " " [https://cisco.com/go/eaops](#)

14 [Done](#)

