



# Cisco Software: Cisco ONE EA 라이선스 이동성

빠른 참조 가이드

# Cisco One EA 라이선스 이동성

저희는 파트너 및 직접 고객이 EA Workspace(EWS)를 통해 Cisco ONE EA 라이선스 포팅 요청을 쉽게 완료할 수 있도록 노력하고 있습니다. 라이선스 포팅이란 대상 디바이스가 다른 계층/버전인 경우 라이선스를 한 디바이스에서 다른 디바이스로 이동하는 것을 의미합니다.

유효한 전송 시나리오에서 EA 고객은 이전에 생성된 라이선스를 한 디바이스에서 다른 디바이스로 이전할 수 있습니다. 이는 EWS에서 추가 소비로 추적되지 않습니다.

EWS는 4단계의 라이선스 포팅 트랜잭션 프로세스(대상 디바이스 선택, 기능 선택, 라이선스 확인, 라이선스 검토)로 고객을 안내합니다.

# Cisco One EA 라이선스 이동성

- 1 EAWS(Enterprise Agreement Workspace)에 로그인하여 적절한 스마트 어카운트 및 가상 어카운트를 선택합니다.
- 2 상단 메뉴에서 Devices(디바이스) 탭을 선택합니다.

The screenshot shows the Cisco Software Central Enterprise Agreements interface. The top navigation bar includes 'Smart Account' (TestELADemo) and 'Virtual Account' (CiscoELA- CiscoONE). The 'Devices' tab is highlighted in the main navigation menu. Below the navigation is a search bar for devices and an 'Add New Devices' button. The main content area displays a table of device information.

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action
test host name...		Mac Address HOSTNAME=76546789		0	0	0	Action ▾
Not Specified	AMP7150	License Key 12:32:46:76:54:33:24		5	5	5	Action ▾
Shivani final	Virtual	Mac Address HOSTNAME=732498274873247234	test final	0	0	0	Action ▾
test 3		Mac Address 234324234324	test 3	0	0	0	Action ▾
Shivani test11	Virtual	Mac Address 3243242434432443	test 11	0	0	0	Action ▾
test 1234		Mac Address 823868326872648324	test 1234	0	0	0	Action ▾
shivani test 4		Mac Address 8739879821739721	test 4	0	0	0	Action ▾

# Cisco One EA 라이선스 이동성

- 3 소스 디바이스 라인에서 Action(작업) 드롭다운 메뉴를 클릭합니다. 이는 라이선스를 전송하고자 하는 디바이스입니다.
- 4 드롭다운 메뉴에서 License Transfer(라이선스 전송)를 선택하여 라이선스 이동성 트랜잭션을 시작합니다.

The screenshot shows the Cisco Software Central interface for Enterprise Agreements. The top navigation bar includes 'Cisco Software Central / Enterprise Agreements', 'Smart Account', and 'Virtual Account CiscoELA-CiscoONE'. Below this is a secondary navigation bar with tabs for 'EAs', 'Devices', 'Transactions', 'Provisioning Requests', 'RTU Transactions', 'Reports', 'Preferences', 'Help', and 'Customer Support'. The 'Devices' tab is active, showing a search bar and an 'Add New Devices' button. The main content area displays a table of devices with columns for Device Name, Model Number, Device Identifiers, Device Description, Transaction, License, Features, and Action. A red circle '3' highlights the 'Action' column header. A red circle '4' highlights the 'License Transfer' option in the expanded dropdown menu for the second device row.

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action
Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2	2	Action ^
Ajinkya	Catalyst 4500 ...	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0CZ	Testing	0	0	License RMA
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DJ		1	1	License Transfer
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DU		0	0	License Resend
Not Specified	ASR1002-HX	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2324Q2CH		1	1	License Download
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2338Q0PT		0	0	Edit Device
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2338Q0PT		0	0	Update Model
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2338Q0PT		0	0	Action v

# Cisco One EA 라이선스 이동성

참고: 선택한 디바이스에 포트에 대한 라이선스 기능이 없는 경우 Action(작업) 메뉴에 라이선스 옵션이 포함되지 않습니다.

Cisco Software Central / Enterprise Agreements

Enterprise Agreements

Smart Account Virtual Account  
CiscoELA-CiscoONE

EAs Devices Transactions Provisioning Requests RTU Transactions Reports Preferences Help Customer Support

View Devices | Search Device(s) Name Or Identifiers Or Device(s) Description  Add New Devices

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action	
Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2	2	Action ▾	
Ajinkya	Catalyst 4500 ...	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0CZ	Testing	0	0	0	Action ▾
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DJ		1	1	1	Action ▾
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DU		0	0	0	Action ▴
Not Specified	ASR1002-HX	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2324Q2CH		1	1	<b>Edit Device</b> <b>Remove Device</b>	
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2338Q0PT		0	0		
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DN		1	1	1	Action ▾

# Cisco One EA 라이선스 이동성

- 5 대상 디바이스를 선택하십시오. 이 디바이스는 소스 디바이스의 라이선스를 포팅하고자 하는 디바이스입니다.
- 6 이제 대상 디바이스로 전송될 소스 디바이스에서 라이선스 기능을 선택할 준비가 되었습니다. Next(다음) 버튼을 클릭하여 2단계로 계속 진행하십시오.

### License Transfer

1 Select Target Device   2 Select Features   3 Verify License   4 Review

Transfer Licences from one device to another device registered with your Cisco Profile.

Selected Source Device:

Serial Number  
23

Select Target Device

Select or Add New Target on which you want to transfer your license.

Search Devices

	Device Name	Model Number	Device Identifiers	Device Description	Transacti...	Lice...
<input type="radio"/>	Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2
<input checked="" type="radio"/>	Not Specified	N9K-C93240...	Serial Number FDO233305XC		0	0
<input type="radio"/>	Not Specified	N9K-C93240...	Host ID .....		1	1

# Cisco One EA 라이선스 이동성

- 7 소스 디바이스에서 포팅하려는 라이선스 기능을 선택합니다.
- 8 Next(다음) 버튼을 클릭하여 3단계로 진행하고 라이선스가 전송되고 있는지 확인합니다.

### License Transfer

Transfer Licences from one device to another device registered with your Cisco Profile.

Select Target Device    Select Features    Verify License    Review

Selected Source Device: \_\_\_\_\_ Target Device: \_\_\_\_\_

Serial Number: 23    Serial Number: FDO233305X C

Select Products and Features

Select Products for which you want to transfer license from.

<input type="checkbox"/>	Feature Name	Product Family	Available Qty	Qty	Trans Date
<input checked="" type="checkbox"/>	MDS_MFGINSTALL	Nexus 4000 Series S...	1	1	2018-Feb-9

Back    Cancel    Next

# Cisco One EA 라이선스 이동성

- 9 라이선스, 소스 디바이스 및 대상 디바이스를 확인합니다. 라이선스 전송 후 선택한 라이선스가 대상 디바이스로 전송됩니다.
- 10 최종 사용자 및 Sent To Recipient(수신자에게 보냄)를 확인 후 필요한 경우 수정합니다.
- 11 확인란을 선택하여 라이선스 약관에 동의하십시오.
- 12 Submit(제출)을 클릭합니다.

License Transfer

Select Target Device    Select Features    Verify License    Review

9

Transfer Licences from one device to another device registered with your Cisco Profile.

UDI Product ID	UDI Version ID	UDI Serial Number	UDI Product ID	UDI Serial Number	UDI Version ID
ISE-VM-K9	V03	FTX12448902	CISCO8765	12765456987	V67

⚠ Post License Transfer, selected licenses will be transferred to target device.

Features  
License Transfer will be done for the following Features

Prod Desc	Sku	L...
Identity Services Engi...	L-ISE-BSE-100=	1

10

User Preferences

Please provide preferences to generate license or request activation.

Notes

Send To \*

End User \*

Include License as an email attachment.     I agree with Terms of the License    [View License Agreement...](#)

11

12

Back    Cancel    Submit



# Cisco One EA 라이선스 이동성

라이선스 포트 확인이 표시됩니다.

- 13 소프트웨어를 다운로드하려는 경우 Download(다운로드) 버튼을 클릭합니다.
- 14 Done(완료) 버튼을 클릭하여 라이선스 포트를 완료합니다.

License Request Status  
The license has been sent to isc **13** **Download**

Thank you for registering your product with Cisco Systems. If you have not received an email within 1 to 3 hours, please open a Service Request using the **EA Licensing Ops Concierge** at .

Use the following transaction ID to view status on the Transactions page.

**Transaction ID:**TRXREQPDHXPSXX - more details are available in the Transactions menu section.

**Note :** Check that Junk/Spam email folders allow email from " "

**14** **Done**

