



シスコソフトウェア： Cisco ONE EA ライセンスポータビリティ クイックリファレンスガイド

Cisco ONE EA ライセンスポータビリティ

パートナーおよび直接取引のお客様が Cisco ONE EA ライセンスの移行リクエストを簡単に送信できるよう、EA Workspace (EAAWS) の整備を進めています。ライセンスの移行とは、ティア/バージョンが異なるデバイス間でライセンスを移行させることを意味します。

EA のお客様は、認められた移行シナリオである限り、以前に生成されたライセンスをデバイス間で移行できます。これは EAWS における追加のライセンス消費としてカウントされません。

EAWS におけるライセンスの移行プロセスは、移行先デバイスの選択、機能の選択、ライセンスの検証、ライセンスの確認という 4 つのステップに分かれています。

Cisco ONE EA ライセンスポータビリティ

- 1 Enterprise Agreement Workspace (EAWS) にログインし、適切なスマートアカウントとバーチャルアカウントを選択します。
- 2 上部のメニューから [デバイス (Devices)] タブを選択します。

The screenshot shows the Cisco ONE EA interface. At the top, there is a navigation bar with the following elements:

- Smart Account: TestELADemo
- Virtual Account: CiscoELA- CiscoONE

The main navigation menu includes: EAs, **Devices** (highlighted with a red box and a '2'), Transactions, Provisioning Requests, RTU Transactions, Reports, Preferences, Help, and Customer Support.

Below the navigation menu is a search bar labeled "View Devices" with the placeholder text "Search Device(s) Name Or Identifiers Or Device(s) Description" and a magnifying glass icon. To the right of the search bar is a blue button labeled "Add New Devices".

The main content area displays a table of devices with the following columns: Device Name, Model Number, Device Identifiers, Device Description, Transaction..., Licens..., Features, and Action.

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action
test host name...		Mac Address HOSTNAME=76546789		0	0	0	Action ▾
Not Specified	AMP7150	License Key 12:32:46:76:54:33:24		5	5	5	Action ▾
Shivani final	Virtual	Mac Address HOSTNAME=732498274873247234	test final	0	0	0	Action ▾
test 3		Mac Address 234324234324	test 3	0	0	0	Action ▾
Shivani test11	Virtual	Mac Address 3243242434432443	test 11	0	0	0	Action ▾
test 1234		Mac Address 823868326872648324	test 1234	0	0	0	Action ▾
shivani test 4		Mac Address 8739879821739721	test 4	0	0	0	Action ▾

Cisco ONE EA ライセンスポータビリティ

- 3 移行元デバイスの行で [アクション (Action)] ドロップダウンメニューをクリックします。移行元デバイスとは、移行するライセンスを使用中のデバイスです。
- 4 ドロップダウンメニューから [ライセンスの転送 (License Transfer)] を選択し、ライセンス移行トランザクションを開始します。

The screenshot shows the Cisco Software Central / Enterprise Agreements interface. The top navigation bar includes "Smart Account" and "Virtual Account CiscoELA-CiscoONE". Below the navigation bar, there are tabs for "EAs", "Devices", "Transactions", "Provisioning Requests", "RTU Transactions", "Reports", "Preferences", "Help", and "Customer Support". The "Devices" tab is active, and a search bar is present with the text "Search Device(s) Name Or Identifiers Or Device(s) Description".

The main content area displays a table of devices. The table has columns for "Device Name", "Model Number", "Device Identifiers", "Device Description", "Transactio...", "Licens...", "Features", and "Action". The "Action" column for the first row is highlighted with a red box and a red circle containing the number 3. The "Action" dropdown menu is expanded, showing options: "License RMA", "License Transfer", "License Resend", "License Download", "Edit Device", and "Update Model". The "License Transfer" option is highlighted with a red box and a red circle containing the number 4.

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action
Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2	2	Action ^
Ajinky	Catalyst 4500 ...	UDI Product ID C1-ASR1002-HX/K9 UDI Serial Number FXS2337Q0CZ	Testing	0	0		License RMA
Not Specified		UDI Product ID C1-ASR1002-HX/K9 UDI Serial Number FXS2337Q0DJ		1	1		License Transfer
Not Specified		UDI Product ID C1-ASR1002-HX/K9 UDI Serial Number FXS2337Q0DU		0	0		License Resend
Not Specified	ASR1002-HX	UDI Product ID C1-ASR1002-HX/K9 UDI Serial Number FXS2324Q2CH		1	1		License Download
Not Specified		UDI Product ID C1-ASR1002-HX/K9 UDI Serial Number FXS2338Q0PT		0	0	0	Edit Device
							Update Model
							Action v

Cisco ONE EA ライセンスポータビリティ

注：選択したデバイスに移行可能なライセンス対象機能がない場合、[アクション (Action)] メニューにはライセンスオプションが含まれません。

Cisco Software Central / Enterprise Agreements

Enterprise Agreements

Smart Account Virtual Account
CiscoELA-CiscoONE

EAs Devices Transactions Provisioning Requests RTU Transactions Reports Preferences Help Customer Support

View Devices | Search Device(s) Name Or Identifiers Or Device(s) Description [Add New Devices](#)

Device Name	Model Number	Device Identifiers	Device Description	Transactio...	Licens...	Features	Action	
Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2	2	Action	
Ajinkya	Catalyst 4500 ...	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0CZ	Testing	0	0	0	Action
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DJ		1	1	1	Action
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DU		0	0	0	Action
Not Specified	ASR1002-HX	UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2324Q2CH		1	1	<div style="border: 2px solid red; padding: 5px; display: inline-block;">Edit Device Remove Device</div>	
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2338Q0PT		0	0		
Not Specified		UDI Product ID C1-ASR1002-HX/K9	UDI Serial Number FXS2337Q0DN		1	1	1	Action

Cisco ONE EA ライセンスポータビリティ

- 5 移行先デバイスを選択します。移行先デバイスとは、ライセンスの移行先となるデバイスです。
- 6 ここでは、移行するライセンス対象機能を選択します。[次へ (Next)] ボタンをクリックしてステップ 2 に進みます。

License Transfer

1 Select Target Device 2 Select Features 3 Verify License 4 Review

Transfer Licences from one device to another device registered with your Cisco Profile.

Selected Source Device:

Serial Number
23

Select Target Device

Select or Add New Target on which you want to transfer your license.

Search Devices

Device Name	Model Number	Device Identifiers	Device Description	Transacti...	Lice...
<input type="radio"/> Not Specified	4X32.5 GBPS ...	Serial Number 23		1	2
<input checked="" type="radio"/> Not Specified	N9K-C93240...	Serial Number FDO233305XC		0	0
<input type="radio"/> Not Specified	N9K-C93240...	Host ID		1	1

Cisco ONE EA ライセンスポータビリティ

- 7 移行元デバイスから移行させるライセンス対象機能を選択します。
- 8 [次へ (Next)] ボタンをクリックしてステップ 3 に進み、ライセンスの転送が進んでいることを確認します。

License Transfer

1 Select Target Device 2 Select Features 3 Verify License 4 Review

Transfer Licences from one device to another device registered with your Cisco Profile.

Selected Source Device: _____ Target Device: _____

Serial Number: 23 Serial Number: FDO233305X
C

Select Products and Features

Select Products for which you want to transfer license from.

<input type="checkbox"/>	Feature Name	Product Family	Available Qty	Qty	Trans Date
<input checked="" type="checkbox"/>	MDS_MFGINSTALL	Nexus 4000 Series S...	1	1	2018-Feb-9

Back Cancel **Next**

Cisco ONE EA ライセンス ポータビリティ

- 9 ライセンス、移行元デバイス、および移行先デバイスを確認します。ライセンスの移行後、選択したライセンスが移行先デバイスに移行されます。
- 10 [エンドユーザ (End User)] および [移行先 (Sent To)] を確認し、必要に応じて変更します。
- 11 チェックボックスをオンにしてライセンス条件に同意します。
- 12 [送信 (Submit)] をクリックします。

License Transfer

Select Target Device Select Features Verify License Review

Transfer Licences from one device to another device registered with your Cisco Profile.

UDI Product ID	UDI Version ID	UDI Serial Number	UDI Product ID	UDI Serial Number	UDI Version ID
ISE-VM-K9	V03	FTX12448902	CISCO8765	12765456987	V67

⚠ Post License Transfer, selected licenses will be transferred to target device.

Features
License Transfer will be done for the following Features

Prod Desc	Sku	L...
Identity Services Engli...	L-ISE-BSE-100=	1

User Preferences

Please provide preferences to generate license or request activation.

Notes

Send To *

End User *

Include License as an email attachment. I agree with Terms of the License [View License Agreement...](#)

Back Cancel Submit

Cisco ONE EA ライセンスポータビリティ

ライセンス移行の検証画面が表示されます。

- 13 ソフトウェアをダウンロードする場合は、[ダウンロード (Download)] ボタンをクリックします。
- 14 [完了 (Done)] ボタンをクリックして、ライセンス移行を完了します。

License Request Status
The license has been sent to you

13 **Download**

Thank you for registering your product with Cisco Systems. If you have not received an email within 1 to 3 hours, please open a Service Request using the EA Licensing Ops Concierge at .

Use the following transaction ID to view status on the Transactions page.

Transaction ID: TRXREQPDHXPSXX - more details are available in the Transactions menu section.

Note : Check that Junk/Spam email folders allow email from " "

14 **Done**

