

```
nexus confi g
====Connecti vi ty between Extender and Nexus 5000====
```

```
swi tch# confi gure termi nal
swi tch(confi g)# fex chassi s 100
```

```
swi tch# confi gure termi nal
swi tch(confi g)# i nterface port-channel 1
swi tch(confi g-i f)# swi tchport mode fex-fabri c
swi tch(confi g-i f)# fex associ ate 100
swi tch(confi g-i f)# exi t
swi tch(confi g)# i nterface ethernet 1/9
swi tch(confi g-i f)# swi tchport mode fex-fabri c
swi tch(confi g-i f)# fex associ ate 100
swi tch(confi g-i f)# channel -group 1
swi tch(confi g-i f)# exi t
swi tch(confi g)# i nterface ethernet 1/10
swi tch(confi g-i f)# swi tchport mode fex-fabri c
swi tch(confi g-i f)# fex associ ate 100
swi tch(confi g-i f)# channel -group 1
swi tch(confi g-i f)# exi t
swi tch(confi g)# i nterface ethernet 1/11
swi tch(confi g-i f)# swi tchport mode fex-fabri c
swi tch(confi g-i f)# fex associ ate 100
swi tch(confi g-i f)# channel -group 1
swi tch(confi g-i f)# exi t
swi tch(confi g)# i nterface ethernet 1/12
swi tch(confi g-i f)# swi tchport mode fex-fabri c
swi tch(confi g-i f)# fex associ ate 100
swi tch(confi g-i f)# channel -group 1
```

```
====End User connecti vi ty(Servers Connected on 2148 Extender)
```

```
swi tch# confi gure termi nal
swi tch(confi g)# i nterface ethernet 100/1/1
swi tch(confi g-i f)# swi tchport mode access
swi tch(confi g-i f)# swi tchport access vl an 5
```

```
swi tch# confi gure termi nal
swi tch(confi g)# i nterface ethernet 100/1/2
swi tch(confi g-i f)# swi tchport mode access
swi tch(confi g-i f)# swi tchport access vl an 6
```

```
swi tch# confi gure termi nal
swi tch(confi g)# i nterface ethernet 100/1/3
swi tch(confi g-i f)# swi tchport mode access
swi tch(confi g-i f)# swi tchport access vl an 7
```

```
swi tch# confi gure termi nal
swi tch(confi g)# i nterface ethernet 100/1/4
swi tch(confi g-i f)# swi tchport mode access
swi tch(confi g-i f)# swi tchport access vl an 8
```

```
====Connecti vi ty between Nexus 5000 and 6509-VSS====
```

```
swi tch# confi gure termi nal
swi tch (confi g)# feature l acp
```

nexus config

```
switch# configure terminal
switch(config)# interface ethernet 1/13
switch(config-if)# switchport mode trunk
switch(config-if)# switchport trunk native vlan 5
switch(config-if)# switchport trunk allow vlan 5-8
switch(config-if)# channel-group 2 mode active
```

```
switch# configure terminal
switch(config)# interface ethernet 1/14
switch(config-if)# switchport mode trunk
switch(config-if)# switchport trunk native vlan 5
switch(config-if)# switchport trunk allow vlan 5-8
switch(config-if)# channel-group 2 mode active
```

```
switch# configure terminal
switch(config)# interface ethernet 1/15
switch(config-if)# switchport mode trunk
switch(config-if)# switchport trunk native vlan 5
switch(config-if)# switchport trunk allow vlan 5-8
switch(config-if)# channel-group 2 mode active
```

```
switch# configure terminal
switch(config)# interface ethernet 1/16
switch(config-if)# switchport mode trunk
switch(config-if)# switchport trunk native vlan 5
switch(config-if)# switchport trunk allow vlan 5-8
switch(config-if)# channel-group 2 mode active
```