

802.3at Inline Power Support Matrix for 89xx/99xx Unified IP Phones & Key Expansion Modules

| Cisco Unified IP Phone Type | First Key Expansion Module | Second Key Expansion Module | Third Key Expansion Module |
|-----------------------------|----------------------------|-----------------------------|----------------------------|
| 8961 | Yes | No | No |
| 9951 w/ camera | Yes | Yes | No |
| 9951 w/o camera | Yes | Yes | No |
| 9971 w/ camera | Yes | Yes | No |
| 9971 w/o camera | Yes | Yes | Yes |

Integrated VXC 21xx 802.3at Inline Power Support Matrix (IP Phone & no Key Expansion Module)

| Cisco Unified IP Phone Type | Basic Configuration (USB Keyboard, USB Mouse, Monitor) | Moderate Configuration (USB Keyboard, USB Mouse, 2 Monitors) | Moderate Configuration (USB Keyboard, USB Mouse, 2 Monitors, USB peripheral, Low Power USB) | Moderate Configuration (USB Keyboard, USB Mouse, 2 Monitors, USB peripheral, Full Power USB) | Maximum Configuration (Bluetooth Dongle for Mouse and Keyboard, USB Mouse, 3 USB peripherals, 2 Monitors, External Speakers, Low Power USB) | Maximum Configuration (Bluetooth Dongle for Mouse and Keyboard, USB Mouse, 3 USB peripherals, 2 Monitors, External Speakers, Full Power USB) |
|-----------------------------|--|--|---|--|---|--|
| 8961 | Yes | Yes | Yes | Yes | Yes | No |
| 9951 w/ camera | Yes | Yes | No | No | No | No |
| 9951 w/o camera | Yes | Yes | Yes | No | Yes | No |
| 9971 w/ camera | Yes | No | No | No | No | No |
| 9971 w/o camera | Yes | Yes | Yes | No | Yes | No |

Standalone VXC 22xx Inline Power Support Matrix

| Inline Power Source | Basic Configuration (USB Keyboard, USB Mouse, Monitor) | Moderate Configuration (USB Keyboard, USB Mouse, 2 Monitors) | Moderate Configuration (USB Keyboard, USB Mouse, 2 Monitors, USB peripheral, Low Power USB) | Moderate Configuration (USB Keyboard, USB Mouse, 2 Monitors, USB peripheral, Full Power USB) | Maximum Configuration (Bluetooth Dongle for Mouse and Keyboard, USB Mouse, 3 USB peripherals, 2 Monitors, External Speakers, Low Power USB) | Maximum Configuration (Bluetooth Dongle for Mouse and Keyboard, USB Mouse, 3 USB peripherals, 2 Monitors, External Speakers, Full Power USB) |
|---------------------|--|--|---|--|---|--|
| 802.3af | Yes | No | No | No | No | No |
| 802.3at | Yes | Yes | Yes | Yes | Yes | Yes |

Notes:

- **802.3af Inline Power will only support a Standalone Virtualization Experience Client 22xx in a Basic Configuration**
- **802.3af Inline Power will not support any Integrated Virtualization Experience Client 21xx configuration**
- **802.3at Inline Power will not support an Integrated Virtualization Experience Client 21xx if a Key Expansion Module is attached to a 89xx/99xx series Unified IP Phone.**
- **A power adapter, PWR-CUBE-4, will support a Standalone Virtualization Experience Client 22xx. A power adapter also supports an Integrated Virtualization Experience Client 21xx attached to a 89xx/99xx series Unified IP Phone and up to 3 Key Expansion Modules.**