

# ALTA DE USUARIO EN CALL MANAGER

## **INTRODUCCION:**


En el siguiente documento se muestra paso a paso el como acceder al equipo Cisco Unified Communications Manager para poder crear un usuario en el sistema para el servicio de telefonía.

En la siguiente presentación también se muestra como crear un END USER para la asociación con el usuario del CUCM.

Cisco Unified CM Console x

← → ↻ 🏠 <https://10.129.220.5/cmadmin/showHome.do> ☆ ☰

Esta página está escrita en inglés ▾ ¿Quieres traducirla? Traducir No No traducir nunca del inglés Configuración ✕

 **Cisco Unified CM Administration**  
For Cisco Unified Communications Solutions

Navigation: Cisco Unified CM Administration ▾ Go


## Cisco Unified CM Administration

**INTRODUCIR  
USERNAME Y  
PASSWORD**

Username  
Administrator

Password  
\*\*\*\*\*

Login Reset



Copyright © 1999 - 2012 Cisco Systems, Inc.  
All rights reserved.

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute or use encryption. Importers, exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at our [Export Compliance Product Report](#) web site.

For information about Cisco Unified Communications Manager please visit our [Unified Communications System Documentation](#) web site.

For Cisco Technical Support please visit our [Technical Support](#) web site.

# Cisco Unified CM Administration

System version: 9.1.1.20000-5

VMware Installation: 2 vCPU Intel(R) Xeon(R) CPU E5-2609 0 @ 2.40GHz, disk 1: 80Gbytes, 4096Mbytes RAM



Last Successful Login: jueves 13 de febrero de 2014 11:59 CST  
Failed Login Attempts 4

Copyright © 1999 - 2012 Cisco Systems, Inc.  
All rights reserved.

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute or use encryption. Importers, exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at our [Export Compliance Product Links](#) web site.

For information about Cisco Unified Communications Manager please visit our [Unified Communications System Documentation](#) web site.

For Cisco Technical Support please visit our [Technical Support](#) web site.

Cisco Unified CM Console: x

← → C ↻ <https://10.129.220.5/ccadmin/showHome.do> ☆ ☰

Navigation Cisco Unified CM Administration Go

adminbarca Search Documentation About Logout

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management ▾ Bulk Administration ▾ Help ▾

- CTI Route Point
- Gateway
- Gateway
- Phone
- Trunk
- Remote Destination
- Device Settings

**Cisco Unified CM Administration**

System version: 9.1.1.20000-5

VMware Installation: 2 vCPU Intel(R) Xeon(R) CPU ES-2, 4096Mbytes RAM

Last Successful Login: jueves 13 de febrero de 2014 13:59 CST  
Failed Login Attempts 4

Copyright © 1999 - 2012 Cisco Systems, Inc.  
All rights reserved.

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute or use encryption. Importers, exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at our [Export Compliance Product Report](#) web site.

For information about Cisco Unified Communications Manager please visit our [Unified Communications System Documentation](#) web site.

For Cisco Technical Support please visit our [Technical Support](#) web site.

<https://10.129.220.5/ccadmin/phoneFindList.do>

Find and List Phones

https://10.129.220.5/cmadmin/phoneFindList.do

Cisco Unified CM Administration  
For Cisco Unified Communications Solutions

Navigation: Cisco Unified CM Administration Go

adminbanco Search Documentation About Logout

System Cal Routing Media Resources Advanced Features Device Application User Management Bulk Administration Help

Find and List Phones Related Links: Actively Logged In Device Report Go

+ Add New

Phone

Find Phone where: Device Name begins with Find Clear Filter

Select item or enter search text

No active query. Please enter your search criteria using the options above.

Add New

SELECCIONAR LA PESTAÑA  
"ADD NEW"  
PARA AGREGAR UN NUEVO USUARIO

Add a New Phone



Status: Ready

Create a phone using the phone type or a phone template

Phone Type\*  
or  
BAT Phone Template\*

Next

\* indicates required field  
\*\* Create a phone template-based phone creation.

- Not Selected --
- Not Selected --
- CTI Port
- CTI Remote Device
- Carrier-integrated Mobile
- Cisco 12 S
- Cisco 12 SP
- Cisco 12 SP+
- Cisco 30 SP+
- Cisco 30 VIP
- Cisco 3905
- Cisco 3911
- Cisco 3951
- Cisco 6901
- Cisco 6911
- Cisco 6921
- Cisco 6941
- Cisco 6945
- Cisco 6961
- Cisco 7902
- Cisco 7905

SE SELECCIONA EL MODELO DEL TELEFONO

Browser window: Add a New Phone  
URL: <https://10.129.220.5/ccmadmin/phoneEdit.do>

**Cisco Unified CM Administration**  
For Cisco Unified Communications Solutions

Navigation: Cisco Unified CM Administration | Go  
admin@cnco | Search Documentation | About | Logout

System | Call Routing | Media Resources | Advanced Features | Device | Application | User Management | Bulk Administration | Help

### Add a New Phone

Related Links: [Back To Find/List](#) | Go

Next

**Status**

Status: Ready

Create a phone using the phone type or a phone template

Phone Type\*  
or  
BAT Phone Template\*

Next

\* indicates required field  
\*\* Create a phone based on a template-based phone creation.

- Cisco 7942
- Cisco 7943
- Cisco 7931
- Cisco 7935
- Cisco 7936
- Cisco 7937
- Cisco 7940
- Cisco 7941
- Cisco 7941G-GE
- Cisco 7942
- Cisco 7945
- Cisco 7960
- Cisco 7961
- Cisco 7961G-GE
- Cisco 7962
- Cisco 7965
- Cisco 7970
- Cisco 7971
- Cisco 7975
- Cisco 7985
- Cisco 8941
- Cisco 8942



Phone Configuration

← → ↻ 🏠 <https://10.129.220.5/ccmadmin/phoneEdit.do> ☆ ☰

**Cisco Unified CM Administration**  
For Cisco Unified Communications Solutions

Navigation | Cisco Unified CM Administration | Go

adminbarco | Search Documentation | About | Logout

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management ▾ Bulk Administration ▾ Help ▾

Phone Configuration Related Links: [Back To Find/List](#) | Go

➔ Next

**Status**

**i** Status: Ready

**Select the type of phone you would like to create**

Product Type: Cisco 7942

Select the device protocol:  SE SELECCIONA EL PROTOCOLO

Next

**i** \* - indicates required item.

**i** \*\* - Create a phone template using the Bulk Administration Tool to enable template-based phone creation.

Phone Configuration x Phone Configuration x

https://10.129.220.5/comadmin/phoneEdit.do

Navigation Cisco Unified CM Administration Go

admin@naco Search Documentation About Logout

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Applications ▾ User Management ▾ Bulk Administration ▾ Help ▾

Phone Configuration Related Links: Back To Find/List Go

Save

Status

Status: Ready

Phone Type

Product Type: Cisco 7942  
Device Protocol: SCCP

Device Information

Device is trusted

MAC Address\*  ← COLOCAR LA MAC DEL TELEFONO QUE SE DESEA AGREGAR

Description

Device Pool\*  [View Details](#)

Common Device Configuration  [View Details](#)

Phone Button Template\*

Softkey Template

Common Phone Profile\*

Calling Search Space

AAR Calling Search Space

Media Resource Group List

User Hold MCH Audio Source

Network Hold MCH Audio Source

Location\*

Phone Configuration x Phone Configuration x

← → ↻ 🔍 <https://10.129.220.5/cnadmin/phoneEdit.do> ☆ ☰

Navigation Cisco Unified CM Administration Go

adminbanco | Search Documentation | About | Logout

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management ▾ Bulk Administration ▾ Help ▾

Phone Configuration Related Links: [Back To FindList](#) Go

Save

**Status**

Status: Ready

**Phone Type**

Product Type: Cisco 7942  
Device Protocol: SCCP

**Device Information**

Device is trusted

MAC Address\*

Description  ← COLOCAR EL NOMBRE DEL USUARIO A QUIEN IRA EL TELEFONO

Device Pool\*  [View Details](#)

Common Device Configuration  [View Details](#)

Phone Button Template\*

Softkey Template

Common Phone Profile\*

Calling Search Space

AAR Calling Search Space

Media Resource Group List

User Hold MOH Audio Source

Network Hold MOH Audio Source

Location\*

Phone Configuration x Phone Configuration x

← → ↻ 🔍 <https://10.129.220.5/camadmin/phoneEdit.do> ☆ ☰

**Cisco Unified CM Administration**  
For Cisco Unified Communications Solutions

Navigation Cisco Unified CM Administration Go

admin@banco Search Documentation About Logout

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management ▾ Bulk Administration ▾ Help ▾

Phone Configuration Related Links: [Back To Find/List](#) Go

Save

**Status**

**Status:** Ready

**Phone Type**

Product Type: Cisco 7942  
Device Protocol: SCCP

**Device Information**

Device is trusted

MAC Address\*

Description

Device Pool\*  [View Details](#)

Common Device Configuration  [View Details](#)

Phone Button Template\*

Softkey Template

Common Phone Profile\*

Calling Search Space

AAR Calling Search Space

Media Resource Group List

User Hold MOH Audio Source

Network Hold MOH Audio Source

SELECCIONAR EL POOL DONDE ESTARA EL TELEFONO

Save

Status: Ready

Phone Type  
Product Type: Cisco 7942  
Device Protocol: SCCP


Device Information

- Device is trusted
- MAC Address\*
- Description
- Device Pool\*
- Common Device Configuration
- Phone Button Template\*
- Softkey Template: < None >
- Common Phone Profile\*: Standard: Common Phone Profile
- Calling Search Space: < None >
- AAR Calling Search Space: < None >
- Media Resource Group List: < None >
- User Hold MOH Audio Source: < None >
- Network Hold MOH Audio Source: < None >

- Standard: 7911 SCCP
- Standard: 7911 SIP
- Standard: 7935
- Standard: 7936
- Standard: 7937
- Standard: 7940 SCCP
- Standard: 7940 SIP
- Standard: 7941 SCCP
- Standard: 7941 SIP
- Standard: 7941G-GE SCCP
- Standard: 7941G-GE SIP
- Standard: 7942G SCCP**
- Standard: 7942G SIP
- Standard: 7945 SCCP
- Standard: 7945 SIP
- Standard: 7960 SCCP
- Standard: 7960 SIP
- Standard: 7961 SCCP
- Standard: 7961 SIP
- Standard: 7961G-GE SCCP
- Standard: 7942G SCCP

[View Details](#)  
[View Details](#)

SE SELECCIONA EL  
TEMPLEATE DE LOS  
BOTONES DEL TELEFONO

 Save

MAC Address*	<input type="text" value="0C2724303DA7"/>
Description	<input type="text" value="RAUL S. BALLESTEROS"/>
Device Pool*	<input type="text" value="DP_Samara"/> <a href="#">View Details</a>
Common Device Configuration	<input type="text" value="&lt; None &gt;"/> <a href="#">View Details</a>
Phone Button Template*	<input type="text" value="Standard 7942G SCCC"/>
Softkey Template	<input type="text" value="&lt; None &gt;"/>
Common Phone Profile*	<input type="text" value="Standard Common Phone Profile"/>
Calling Search Space	<input type="text" value="&lt; None &gt;"/>
AAR Calling Search Space	<input type="text" value="&lt; None &gt;"/>
Media Resource Group List	<input type="text" value="&lt; None &gt;"/>
User Hold MOH Audio Source	<input type="text" value="&lt; None &gt;"/>
Network Hold MOH Audio Source	<input type="text" value="&lt; None &gt;"/>
Location*	<input type="text" value="Hub_None"/>
AAR Group	<input type="text" value="&lt; None &gt;"/>
User Locale	<input type="text" value="&lt; None &gt;"/>
Network Locale	<input type="text" value="&lt; None &gt;"/>
Built In Bridge*	<input type="text" value="Predeterminado"/>
Privacy*	<input type="text" value="Predeterminado"/>
Device Mobility Mode*	<input type="text" value="Predeterminado"/> <a href="#">View Current Device Mobility Settings</a>
Owner User ID	<input type="text" value="&lt; None &gt;"/> <input type="button" value="Find"/>

Phone Configuration x Phone Configuration x

← → C f <https://10.129.220.5/ccmadmin/phoneEdit.do> ☆ ☰

Navigation Cisco Unified CM Administration Go

adminbanco Search Documentation About Logout

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management ▾ Bulk Administration ▾ Help ▾

Phone Configuration Related Links: [Back To Find/List](#) Go

Save

MAC Address*	DC2724303DA7
Description	RAUL S. BALLESTEROS
Device Pool*	DP_Samara <a href="#">View Details</a>
Common Device Configuration	< None > <a href="#">View Details</a>
Phone Button Template*	Standard 7942G SCCP
Softkey Template	< None >
Common Phone Profile*	Standard Common Phone Profile
Calling Search Space	< None >
AAR Calling Search Space	< None >
Media Resource Group List	< None >
User Hold MOH Audio Source	< None > MRG_Samara
Network Hold MOH Audio Source	MRG_Xalapa < None >
Location*	Hub_None
AAR Group	< None >
User Locale	< None >
Network Locale	< None >
Built In Bridge*	Predeterminado
Privacy*	Predeterminado
Device Mobility Node*	Predeterminado <a href="#">View Current Device Mobility Settings</a>
Owner User ID	< None > <input type="button" value="Find"/>

SE SELECCIONA A QUE GRUPO PERTENECE



Standard Profile	standard / rj4u SLLP
Softkey Template	< None >
Common Phone Profile*	Standard Common Phone Profile
Calling Search Space	< None >
AAR Calling Search Space	< None >
Media Resource Group List	mlopez mmartinez mmatus mmedina mmendez mmorales mmunoz mno mnolesco moagular molascaga montiveros mpne mpiane mnoa msanchez msanchezj mtomes mvalencia
User Hold MCH Audio Source	
Network Hold MCH Audio Source	
Location*	
AAR Group	
User Locale	
Network Locale	
Built In Bridge*	
Privacy*	
Device Mobility Node*	
Owner User ID	rsanchez
Phone Personalization*	Predeterminado
Services Provisioning*	Predeterminado
Phone Load Name	
Single Button Range	Predeterminado
Trunk Access Lines	Predeterminado

AGREGAR EL USUARIO CALLING SEARCH SPACE

[View Current Device Mobility Settings](#)

Find





MAC Address*	<input type="text" value="DC2724303DA7"/>
Description	<input type="text" value="RAUL S. BALLESTEROS"/>
Device Pool*	<input type="text" value="DP_Samara"/> <a href="#">View Details</a>
Common Device Configuration	<input type="text" value="&lt; None &gt;"/> <a href="#">View Details</a>
Phone Button Template*	<input type="text" value="Standard 7942G SCCP"/>
Softkey Template	<input type="text" value="&lt; None &gt;"/>
Common Phone Profile*	<input type="text" value="Standard Common Phone Profile"/>
Calling Search Space	<input type="text" value="&lt; None &gt;"/>
AAR Calling Search Space	<input type="text" value="&lt; None &gt;"/>
Media Resource Group List	<input type="text" value="MRGL_Samara"/>
User Hold MOH Audio Source	<input type="text" value="&lt; None &gt;"/>
Network Hold MOH Audio Source	<input type="text" value="&lt; None &gt;"/>
Location*	<input type="text" value="Hub_None"/>
AAR Group	<input type="text" value="&lt; None &gt;"/>
User Locale	<input type="text" value="&lt; None &gt;"/>
Network Locale	<input type="text" value="&lt; None &gt;"/>
Built In Bridge*	<input type="text" value="Español, República de Colombia"/>
Privacy*	<input type="text" value="Predeterminado"/>
Device Mobility Mode*	<input type="text" value="Predeterminado"/> <a href="#">View Current Device Mobility Settings</a>
Owner User ID	<input type="text" value="&lt; None &gt;"/> <input type="button" value="Find"/>

SELECCIONAR EL IDIOMA

Find and List Users - Google Chrome

https://10.129.220.5/ccadmin/userFindList.do?whereClause=tkuserprofile%20=%201&sqJoin=

### Find and List Users

Select All Clear All Add Selected Close

**Status**

2 records found

**User (1 - 2 of 2)** Rows per Page: 50

Find User where User ID contains sánchez Find Clear Filter

User ID	First Name	Last Name	Department	User Status
rsanchez	RAUL	SANCHEZ		Active Local User
rsanchezb	Saul	Sanchez Balentoro		Active LDAP Synchronized User

Select All Clear All Add Selected Close

Navigation Cisco Unified CM Administration Go

adminbanco Search Documentation About Logout

Related Links: Back To Find/List Go

SE SALVA LO REALIZADO Y AL BUSCAR AL USUARIO YA LO PODEMOS ENCONTRAR.

Ability Settings

Phone Load Name

Single Button Barge Predefinido

Join Across Lines

Save X Delete Copy Reset Apply Config Add New

AL INGRESAR AL USUARIO PODEMOS HACER MODIFICACIONES. EN ESTE CASO SE DEBE CONFIGURAR LA LINEA O LINEAS QUE UTILIZARA EL TELEFONO.

Status  
Status: Ready

- Association Information
- Modify Button Items
- 1 Line [1] - 7705 in P. Llamadas, Extensiones, Samara
  - 2 Line [2] - Add a new DN
  - Unassigned Associated Items -----
  - 3 Add a new SURF
  - 4 Add a new B/F SD
  - 5 Add a new SD
  - 6 Add a new B/F Directed Call Park
  - 7 Retrolia
  - 8 Apencer llamada
  - 9 Captura de llamada
  - 10 Lista de conf.
  - 11 Conferencia
  - 12 No molestor
  - 13 FinJem.
  - 14 Desviar todas

Phone Type

Product Type: Cisco 7942  
Device Protocol: SCCP

Device Information

Registration: Registered with Cisco Unified Communications Manager 10.129.220.5

IP Address: [10.129.112.55](#)

Active Load ID: SCCP42-9-3-15R1-1S

Download Status: Unknown

Device is Active

Device is trusted

MAC Address\*:

Description:

Device Pool\*:  [View Details](#)

Common Device Configuration:  [View Details](#)

Phone Button Template\*:

Softkey Template:

Common Phone Profile\*:

Calling Search Space:

Phone Configuration x Directory Number Config x

← → ↻ 🔍 <https://10.129.220.5/ccmadmin/directoryNumberEdit.do?key=dc265fed-e262-0fbc-d6c7-adb0906ca141&mapkey=fcbf656b-f5f5-1801-2b20-0c91d4c98ee7&devicekey>

**Cisco Unified CM Administration**  
For Cisco Unified Communications Solutions

Navigation Cisco Unified CM Administration Go

admin@banco Search Documentation About Logout

System Call Routing Media Resources Advanced Features Device Application User Management Bulk Administration Help

Directory Number Configuration Related Links: [Configure Device \(SEP0C27243030A7\)](#) Go

Save X Delete Reset Apply Config Add New

**Status**

Status: Ready

**Directory Number Information**

Directory Number\* 7745

Route Partition P\_Llamadas\_Extensiones\_Samara

Description RAUL S. BALLESTEROS

Alerting Name RAUL S. BALLESTEROS

ASCII Alerting Name RAUL S. BALLESTEROS

Allow Control of Device from CTI

Associated Devices

SEP00007745
SEP0C27243030A7
CSFrsanchezb
TABRSANCHEZB
TCFRSANCHEZB

▼ ▲

Dissociate Devices

SE AGREGAN LOS DATOS.

Edit Device

Edit Line Appearance

**Directory Number Settings**

Voice Mail Profile VoiceMailConsulbanco (Choose <None> to use system default)

Calling Search Space CSS\_Samara\_FAC

Save Delete Reset Apply Config Add New

UNASSIGNED USER LIST

**Directory Number Settings**

Voice Mail Profile: VoiceMailConsuabanco (Choose <None> to use system default) ←

Calling Search Space: CSS\_Samara\_FAC ←

BLF Presence Group\*: Standard Presence group

User Hold MOH Audio Source: 1-SampleAudioSource ←

Network Hold MOH Audio Source: 1-SampleAudioSource ←

Auto Answer\*: Auto Answer Off

Reject Anonymous Calls

Las siguientes casillas nos sirven para el mensaje de correo y cuáles serán los audios del teléfono.

**Directory URIs**

Primary	URI	Partition	Edit/Remove
<input checked="" type="checkbox"/>	spirsanchezb@consuabego.com	Directory URI	<a href="#">Edit/Remove</a>
	<input type="text"/>	<None>	<input type="button" value=""/>

**AAR Settings**

	Voice Mail	AAR Destination Mask	AAR Group
AAR	<input type="checkbox"/> or	<input type="text"/>	<None>

Save this destination in the call forwarding history

Save Delete Reset Apply Config Add New

Retain this destination in the call forwarding history

Se configuran los parámetros de las llamadas.

Call Forward and Call Pickup Settings

	Voice Mail	Destination	Calling Search Space
Calling Search Space Activation Policy			Utilizar configuración predeterminada del sistema
Forward All	<input type="checkbox"/> or		CSS_VN_Consubanco
Secondary Calling Search Space for Forward All			CSS_VN_Consubanco
Forward Busy Internal	<input checked="" type="checkbox"/> or		CSS_VN_Consubanco
Forward Busy External	<input checked="" type="checkbox"/> or		CSS_VN_Consubanco
Forward No Answer Internal	<input checked="" type="checkbox"/> or		CSS_VN_Consubanco
Forward No Answer External	<input checked="" type="checkbox"/> or		CSS_VN_Consubanco
Forward No Coverage Internal	<input type="checkbox"/> or		< None >
Forward No Coverage External	<input type="checkbox"/> or		< None >
Forward on CTI Failure	<input type="checkbox"/> or		< None >
Forward Unregistered Internal	<input checked="" type="checkbox"/> or		CSS_VN_Consubanco
Forward Unregistered External	<input checked="" type="checkbox"/> or		CSS_VN_Consubanco
No Answer Ring Duration (seconds)		18	
Call Pickup Group		< None >	

Save Delete Reset Apply Config Add New

Party Entrance Tone Predeterminado

Line 1 on Device SEP0C2724303DA7


	Value	Update Shared Device Settings
Display (Caller ID)	RAUL S. BALLESTEROS <small>Display text for a line appearance is intended for displaying text such as a name instead of a directory number for calls. If you specify a number, the person receiving a call may not see the proper identity of the caller.</small>	<input type="checkbox"/>
ASCII Display (Caller ID)	RAUL S. BALLESTEROS	<input type="checkbox"/>
Line Text Label	RAUL S. BALLESTEROS	<input type="checkbox"/>
ASCII Line Text Label	RAUL S. BALLESTEROS	<input type="checkbox"/>
External Phone Number Mask		<input type="checkbox"/>
Visual Message Waiting Indicator Policy	Use System Policy	<input type="checkbox"/>
Audible Message Waiting Indicator Policy	Predeterminado	<input type="checkbox"/>
Ring Setting (Phone Idle)	Use System Default	<input type="checkbox"/>
Ring Setting (Phone Active)	Use System Default <small>Applies to this line when any line on the phone has a call in progress.</small>	<input type="checkbox"/>
Call Pickup Group Audio Alert Setting(Phone Idle)	Use System Default	<input type="checkbox"/>
Call Pickup Group Audio Alert Setting(Phone Active)	Use System Default	<input type="checkbox"/>
Recording Option	Grabación de llamadas deshabilitada	<input type="checkbox"/>

Se agrega el nombre del usuario. Esta información aparecerá en el display del teléfono y cuando otro usuario conteste la llamada.

Directory Number Configuration

Related Links: [Configure Device \(SEP0C2724303DA7\)](#) Go

 Save  Delete  Reset  Apply Config  Add Item

**Status**  
 Update successful  
Se salvan los cambios para que se apliquen en el dispositivo.

Directory Number Information

Directory Number\*

Route Partition

Description

Alerting Name

ASCII Alerting Name

Loading, please wait.

Allow Control of Device from CTI

Associated Devices

▼ ▲

Dissociate Devices

[Edit Device](#)  
[Edit Line Appearance](#)

Directory Number Settings

Voice Mail Profile  (Choose <None> to use system default)

Calling Search Space



Phone Configuration x Directory Number Config x

Navigation Cisco Unified CM Administration Go

admin@cnca Search Documentation About Logout

System Call Routing Media Resources Advanced Features Device Application User Management Bulk Administration Help

### Directory Number Configuration

Save Delete Revert Apply Config Add New

Status Update successful

Application User  
End User  
UserPhone Add  
SP Realm  
User Settings

Related Links: Configure Device (SEP0C2724303DA7) Go

#### Directory Number Information

Directory Number\* 7745

Route Partition P\_Lamedas\_Extensiones\_Samara

Description RALL S. BALLESTEROS

Alerting Name RALL S. BALLESTEROS

ASCII Alerting Name RALL S. BALLESTEROS

Allow Control of Device from CTI

Associated Devices

- SEP00007745
- SEP0C2724303DA7
- CSFfrancheto
- TABRSAVQHEZB
- TCTRSAVQHEZB

▼ ▲

Disassociate Devices

Edit Device

Edit Line Appearance

Después de guardar y haber dado de alta el dispositivo. Nos vamos a agregarlo al END USER.

#### Directory Number Settings

Voice Mail Profile VoiceMailConsuenco (Choose <None> to use system default)

Phone Search Range

Phone Configuration x Find and List Users x


← → ↻ 🏠 <https://10.129.220.5/ccmadmin/userFindList.do?recCnt=50&colCnt=4> ☆ ☰

Navigation Cisco Unified CM Administration Go


adminbanco | Search Documentation | About | Logout

System • Call Routing • Media Resources • Advanced Features • Device • Application • User Management • Bulk Administration • Help



### Find and List Users

 Add New



Status

 0 records found

User Rows per Page 50 ▼

Find User where First name ▼ contains ▼  Find Clear filter  

No active query. Please enter your search criteria using the options above.

En esta ventana podemos buscar el END USER o Crear un nuevo END USER para asociarlo a un dispositivo.

**Find and List Users**

+ Add New

**Status**

 0 records found

**User** Rows per Page 50 ▾

Find User where First name ▾ contains ▾

No active query. Please enter your search criteria using the options above.

Loading, please wait.

End User Configuration

Related Links: [Back to Find List Users](#) Go

Save Delete Add New

Status

Status: Ready

User Information

User Status	Active Local User
User ID*	<input type="text" value="rsanchez"/>
Password	<input type="password"/> <a href="#">Edit Credential</a>
Confirm Password	<input type="password"/>
PIN	<input type="password"/> <a href="#">Edit Credential</a>
Confirm PIN	<input type="password"/>
Last name*	<input type="text" value="SANCHEZ"/>
Middle name	<input type="text"/>
First name	<input type="text" value="RALL"/>
Directory URI	<input type="text"/>
Telephone Number	<input type="text" value="5500"/>
Mail ID	<input type="text"/>
Manager User ID	<input type="text"/>
Department	<input type="text"/>
User Locale	< None >
Associated PC	<input type="text"/>

Aquí se tienen que introducir los datos del usuario y la extensión a la que estará asociado.

Phone Configuration x End User Configuration x

← → C <https://10.129.220.5/ccmadmin/userEdit.do?key=1c8cdc2-117f-c949-d92b-5828f9cee6a> ☆ ☰

**Cisco Unified CM Administration** For Cisco Unified Communications Solutions Navigation Cisco Unified CM Administration Go

adminbanca | Search Documentation | About | Logout

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management ▾ Bulk Administration ▾ Help ▾

**End User Configuration** Related Links: [Back to Find List Users](#) Go

Save **X** Delete + Add New

---

**Service Settings**

Home Cluster

Enable User for Unified CM IM and Presence (Configure IM and Presence in the associated UC Service Profile)

UC Service Profile: Use Default [View Details](#)

---

**Device Information**

Controlled Devices:

Available Profiles:

CTI Controlled Device Profiles:

**Device Association** ← **Line Appearance Association for Presence**

En esta ventana se asocia el dispositivo o extensión.

---

**Extension Mobility**

Available Profiles:

 Save  Delete  Add New

▼ ▲

CTI Controlled Device Profiles

**Extension Mobility**

Available Profiles

▼ ▲

Controlled Profiles

Default Profile

BU Presence Group\*

SUBSCRIBE Calling Search Space

Allow Control of Device from CTI

Enable Extension Mobility Cross Cluster

**Directory Number Associations**

Primary Extension

End User Configuration x Rolling Stones - gratis x

← → ↻ ↗ <https://10.10.1.210:8443/ccmadmin/userEdit.do?key=f9fc1299-a27f-4c91-aca4-f789629586b4> ☆ ☰

**Cisco Unified CM Administration**  
Para soluciones de Cisco Unified Communications

Navigation Cisco Unified CM Administration

UNAdministrator | Search Documentation | About | Logout

System • Call Routing • Media Resources • Advanced Features • Device • Application • User Management • Bulk Administration • Help •

End User Configuration Related Links: [Back to Find List Users](#) Go

**Start**

Controlled Profiles

Default Profile: -- Not Selected --

Presence Group: Standard Presence group

SUBSCRIBE Calling Search Space: < None >

Allow Control of Device from CTI

Enable Extension Mobility Cross Cluster

**Directory Number Associations**

Primary Extension: 2503 in P\_Ext\_DF

IPCC Extension: < None >

Se tiene que asociar a la extensión.

**Mobility Information**

Enable Mobility

Primary User Device: < None >

Enable Mobile Voice Access

Maximum Wait Time for Desk Pickup: 0000

Remote Destination Limit: 4

Remote Destination Profiles: MOBILE\_CM

Phone Configuration x End User Configuration x

← → ↻ 🏠 <https://10.129.220.5/crnadmin/userEdit.do?key=1c8ock2-117f-c949-d92b-5828fc9cee6a> ☆ ☰

**Cisco Unified CM Administration** For Cisco Unified Communications Solutions Navigation Cisco Unified CM Administration Go

admin@cnco Search Documentation About Logout

System ▾ Call Routing ▾ Media Resources ▾ Advanced Features ▾ Device ▾ Application ▾ User Management ▾ Bulk Administration ▾ Help ▾

**End User Configuration** Related Links: [Back to Find List Users](#) Go

📁 Save ✖ Delete ➕ Add New

---

**Mobility Information**

Enable Mobility

Enable Mobile Voice Access

Maximum Wait Time for Desk Pickup

Remote Destination Limit

Remote Destination Profiles

[View Details](#)

---

**Multilevel Precedence and Preemption Authorization**

MLPP User Identification Number

MLPP Password

Confirm MLPP Password

MLPP Precedence Authorization Level

---

**CAPF Information**

Associated CAPF Profiles

[View Details](#)

---

**Permissions Information**



End User Configuration Related Links: Back to Find List Users Go

Save Delete Add New

MLPP Password  
Confirm MLPP Password  
MLPP Precedence Authorization Level: Routine

CAPE Information  
Associated CAPE Profiles  
Loading, please wait.  
View Details

Permissions Information  
Groups  
Add to Access Control Group  
Remove from Access Control Group  
View Details  
Roles  
View Details

Save Delete Add New

i \* indicates required item.

### Find and List Users

Add New Select All Clear All Delete Selected

**Status**

2 records found

User (1 - 2 of 2) Rows per Page 50

Find User where User ID contains rsanchez

<input type="checkbox"/>	User ID *	First Name	Last Name	Department	User Status
<input type="checkbox"/>	<a href="#">rsanchez</a>	Raul	SANCHEZ		Active Local User
<input type="checkbox"/>	<a href="#">rsanchezb</a>	Raul	Sanchez Bailestano		Active LDAP Synchronized User

Ya está agregado el END USER.