

Cisco WebEx Telepresence Supported Devices | Quick Comparison Matrix



	Cisco Jabber Video	Cisco TelePresence System EX60	Cisco TelePresence System EX90	Cisco TelePresence System Quick Set SX20	Cisco TelePresence System Quick Set C20	Cisco TelePresence System Codec C40, Profile 42 with C40, Profile 55 with C40	Cisco TelePresence System Codec C60, Profile 55 with C60, Profile 55 Dual with C60, Profile 65 with C60	Cisco TelePresence System Codec C90, Profile 65 Dual with C90	Cisco TelePresence System MX200	Cisco TelePresence System MX300	Cisco TelePresence System VX CA
Environment	Mobile video worker	Personal TelePresence unit	Personal TelePresence unit	Conference Room TelePresence unit	Conference Room TelePresence unit	Conference Room TelePresence unit	Conference room TelePresence unit	Conference room TelePresence unit	Conference room TelePresence unit	Conference Room TelePresence unit	Mobile telemedicine unit
Available subscription options	Cisco Jabber Video	Premium	Premium	Premium	Premium	Premium	Premium	Premium	Premium	Premium	Premium
User interface	Windows/Macintosh software client Cisco Jabber for iPad software client	Cisco TelePresence Touch	Cisco TelePresence Touch	TRC5 remote control	TRC5 remote control	TRC5 remote control (Codec C40), Cisco TelePresence Touch (Profile 42 with C40, Profile 55 with C40)	TRC5 remote control (Codec C60), Cisco TelePresence Touch (Profile 55 with C60, Profile 55 Dual with C60, Profile 65 with C60)	TRC5 remote control (Codec C90), Cisco TelePresence Touch (Profile 65 Dual with C90)	Cisco TelePresence Touch	Cisco TelePresence Touch	<ul style="list-style-type: none"> One-touch control panel TRC5 remote control
Data presentation	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
MultiSite	No	No	3 parties and self if optional MultiSite feature is installed	3 parties and self if optional MultiSite feature is installed	No	3 parties and self if optional MultiSite feature is installed	3 parties and self if optional MultiSite feature is installed	3 parties and self if optional MultiSite feature is installed	No	No	No
Camera	Any user-provided, PrecisionHD USB camera is optimal	PrecisionHD 1080p camera	PrecisionHD 1080p camera	PrecisionHD 1080p camera	PrecisionHD 1080p camera	PrecisionHD 1080p camera	PrecisionHD 1080p camera	PrecisionHD 1080p camera	PrecisionHD 1080p camera	PrecisionHD 1080p camera	PrecisionHD 1080p camera
Display	Windows/Macintosh/iPad model dependent	21.5" LCD monitor (with LED backlight)	24" LCD monitor	User-provided display	User-provided display	<ul style="list-style-type: none"> User-provided display (C40) 42" integrated display (Profile 42) 55" integrated display (Profile 55) 	<ul style="list-style-type: none"> User-provided display (C60) 55" integrated display (Profile 55) 55" integrated dual display (Profile 55 Dual) 65" integrated display (Profile 65) 	<ul style="list-style-type: none"> User-provided display (C90) 65" integrated dual display (Profile 65 Dual) 	42" integrated display	55" integrated display	24" widescreen LCD/LED backlight monitor
Microphone	Windows/Macintosh/iPad model dependent	Built-in	Built-in	Cisco TelePresence Table Microphone	Cisco Precision Microphone 20	(Optional) 1 x omnidirectional microphone w/ cables, sold separately	(Optional) 1 x omnidirectional microphone w/ cables, sold separately	(Optional) 2 x omnidirectional microphone w/cables, sold separately	Built-in	2 x Built-in	Built-in
Video inputs	None	1 x DVI-I	1 x DVI-I and 1 x HDMI	1 x DVI-I and 1 x HDMI	1 x DVI-I and 1 x HDMI	<ul style="list-style-type: none"> 1 x DVI-I 2 x HDMI 1 x S-Video/Composite input (BNC connectors) 	<ul style="list-style-type: none"> 2 x DVI-I 2 x HDMI 1 x YPBPR 1 x Composite 	<ul style="list-style-type: none"> 2 x DVI-I 4 x HDMI 4 x HD-SDI 2 x YPBPR 1 x S-Video/Composite 	1 x DVI-I	1 X DVI-I	<ul style="list-style-type: none"> 3 x S-video (4-pin mini din connectors) 3 x composite (RCA connectors) 1 x PAL/NTSC 3 x HDMI (one designated as main camera input) 2 x DVI-I (one designated as PC input)
Video outputs	Windows/Macintosh/iPad model dependent	None	1 x HDMI output	2 x HDMI output	2 x HDMI output	1 x DVI-I and 1 x HDMI	1 x DVI-I and 1 x HDMI	2 x DVI-I and 2 x HDMI	None	None	<ul style="list-style-type: none"> 1 x Composite (RCA connector) 1 x HDMI (main display)
Audio inputs	Windows/Macintosh/iPad model dependent	1 x 3.5mm line-in jack for PC or other audio source	<ul style="list-style-type: none"> 1 x 3.5mm line-in jack for PC or other audio source 1 x HDMI input Support for Cisco Precision Microphone 20 	<ul style="list-style-type: none"> 2 x Microphone, 4-pin MiniJack 1 x minijack for line in (stereo) 1 x audio in from camera (HDMI) 	<ul style="list-style-type: none"> 2 x Microphone, 4-pin MiniJack (for Cisco Precision Microphone 20) 2 x RCA/phono (mixed to mono) 	<ul style="list-style-type: none"> 2 x Microphone, 48V Phantom Powered XLR connector each with separate echo cancellers and noise reduction; all microphones can be set for balanced line level 2 x RCA/phono, line level, stereo PC input, configurable to 2 x RCA/phono, line level, mono auxiliary/DVD input 1 x HDMI, digital, stereo PC/DVD inputs 	<ul style="list-style-type: none"> 4 x microphone, 48V phantom powered, XLR connector each with separate echo cancellers and noise reduction, all microphones can be set for balanced line level 2 x RCA/Phono, Line Level: Stereo PC input, configurable to 2 x RCA/Phono, Line Level: Mono auxiliary/DVD input 1 x HDMI, digital: Stereo PC/DVD inputs 	<ul style="list-style-type: none"> 8 x microphones, 48V phantom powered, XLR connector each with separate echo cancellers and noise reduction, and all microphones can be set for balanced line level 2 x RCA/Phono, Line Level: Stereo PC input 2 x RCA/Phono, Line Level: Stereo auxiliary/DVD input 2 x HDMI, digital: Stereo PC/DVD inputs 	RCA PC audio input	RCA PC audio input	<ul style="list-style-type: none"> 2 x Microphone, 4-pin MiniJack with mixed monosignal with 1 echo canceller 2 x 3.5-mm audio inputs, line level: 1 back of system of PC audio, 1 front of system for electronic audio systems
Audio outputs	Windows/Macintosh/iPad model dependent	<ul style="list-style-type: none"> Integrated stereo front speakers 2 x 3.5mm jack for headset 	<ul style="list-style-type: none"> Integrated stereo front speakers Integrated subwoofer 2 x 3.5mm jack for headset HDMI output 	<ul style="list-style-type: none"> 1 x minijack for line out (stereo) 1 x HDMI (digital main audio) 	<ul style="list-style-type: none"> 2 x RCA/phono (dual mono), 1 x HDMI (digital main audio) User-provided speakers 	<ul style="list-style-type: none"> 2 x RCA/phono, line level, stereo max audio, configurable to S/PDIF or 2 x RCA/phono, line level, mono to recording device 1 x HDMI, digital, stereo main audio User-provided speakers (C40) Integrated speakers (Profile) 	<ul style="list-style-type: none"> 2 x RCA/Phono, line level, stereo main audio, configurable to S/PDIF or 2 x RCA/Phono, line level, and mono to recording device 1 x HDMI, digital, and stereo main audio User-provided speakers (C60) Integrated speakers (Profile) 	<ul style="list-style-type: none"> 2 x XLR, balanced line level, and stereo main audio 2 x RCA/Phono, line level, and stereo main audio, configurable to S/PDIF 2 x RCA/Phono, line level, and stereo to recording device 1 x HDMI, digital, and stereo main audio 1 x HDMI, digital, and stereo to recording device User-provided speakers (C90) Integrated speakers (Profile) 	RCA audio output	RCA audio output	1 x 1/4 Phono line level (headphones)
Network interfaces	Windows/Macintosh/iPad model dependent	<ul style="list-style-type: none"> Internal 2-port Ethernet switch 1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps for PC 1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps for LAN 	<ul style="list-style-type: none"> Internal 2-port Ethernet switch 1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps for PC 1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps for LAN 	1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps	1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps	2 x LAN/Ethernet (RJ-45) 10/100/1000Mbps	1 x LAN/Ethernet (RJ-45) 10/100/1000 Mbit	2 x LAN/Ethernet (RJ-45) 10/100/1000 Mbit	1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps	1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps	1 x LAN/Ethernet (RJ-45) 10/100/1000Mbps
Video quality	720p30 (best with PrecisionHD camera)	1080p30	1080p30	1080p60	1080p30	1080p30	1080p60	1080p60	1080p30	1080p30	1080p60